

Project: IEEE P802.15 Working Group for Wireless Personal Area Networks (WPANs)

Submission Title: [**Comment Resolutions related to frequency deviation definition**]

Date Submitted: [January xx, 2011]

Source: [Hiroshi Harada¹, Fumihide Kojima¹, Sum Chin Sean¹, Takaaki Hatauchi², Kazuo Kubo³, Tomonori Sato⁴, Kentaro Sakamoto⁵, Aiichiro Kashiwagi⁶, Takahiro Banno⁷, Hirohito Nishiyama⁸]

Company [1NICT, 2Fuji Electric, 3Panasonic, 4Toshiba Toko Meter Systems, 5Tokyo Gas, 6Osaka Gas, 7Toho Gas, 8Mitsubishi Electric Corp.]

Address [13-4, Hikari-no-oka, Yokosuka-shi, Kanagawa, 239-0847, Japan]

Voice: [1+81-46-847-5074]

FAX: [1+81-46-847-5440]

E-Mail: [f-kojima@nict.go.jp, harada@nict.go.jp]

Re: [TG4g comment resolution]

Abstract: [Comment resolutions related to the definition of frequency deviation]

Notice: This document has been prepared to assist the IEEE P802.15. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.

Release: The contributor acknowledges and accepts that this contribution becomes the property of IEEE and may be made publicly available by P802.15.

Summary

This document describes the proposed resolution on the comments related to the definition of frequency deviation.

The following comment is addressed; CID #486, #487 and #488.

Comments and proposed resolutions

CID #486: In Figure 65o the units on the y-axis should be $\Delta 0.5f$, $0.25 \cdot \Delta f$, $-0.25\Delta f$, $-0.5\Delta f$. On the x-axis the units should be $-T_s$, $-0.5T_s$, $0.5T_s$, T_s .

CID #488: In Figure 65p the units on the y-axis should be $0.5\Delta f$, $0.25 \cdot \Delta f$, $-0.25\Delta f$, $-0.5\Delta f$. On the x-axis the units should be $-T_s$, $-0.5T_s$, $0.5T_s$, T_s .

Proposed resolution (for both CID #486 and #488): Accept in principle.

For the x-axis, change the units as proposed. For the y-axis no changes required (resolution to CID #487 to solve the issue)

CID #487: In table 75c the the frequency deviation for 2-level should be $0.5 \cdot \Delta f$, $-0.5\Delta f$. For 4-level the frequency deviation should be $0.5\Delta f$, $0.3333 \cdot \Delta f$, $-0.3333\Delta f$, $-0.5\Delta f$.

Proposed resolution: Accept in principle.

Revise the table 75c as shown in the next slide (instead of using Δf , f_{dev} is used as a unit). In addition, replace the texts in 6.12a.1.2 (Bit-to-symbol mapping) with those in slide 5.

Proposed revision: Table 75c – MR-FSK symbol encoding

Red letters show the revised parts

2-level	
Symbol (binary)	Frequency Deviation
0	$-1 * f_{dev}$
1	$+1 * f_{dev}$
4-level	
Symbol (binary)	Frequency Deviation
01	$-1 * f_{dev}$
00	$-1/3 * f_{dev}$
10	$+1/3 * f_{dev}$
11	$+1 * f_{dev}$

Proposed revision: 6.12a.1.2 Bit-to-symbol mapping

Red letters show the revised parts

The nominal frequency deviation shall be the (symbol rate) \times (modulation index) / 2. The symbol encoding for both filtered 2-level and 4-level FSK modulation is shown in Table 75c, where they are described by function of the maximum frequency deviation, f_{dev} , that is equal to the nominal frequency deviation for filtered 2-FSK and is equal to (nominal frequency deviation) \times 3 for filtered 4-FSK.

For filtered 4FSK modulation, two bits shall be mapped to four frequency deviation levels for the PHR and PSDU. For the SHR, bit 0 and bit 1 shall be mapped to the lowest ~~$(-3 \times \Delta f)$~~ and the highest ~~$(+3 \times \Delta f)$~~ frequency deviations respectively. The symbol rate shall be the same for the entire PPDU. PPDU encoding for filtered 4FSK is shown in Figure 65n.