

1  
2  
3

**IEEE P802.15**  
**Wireless Personal Area Networks**

---

Project	IEEE P802.15 Working Group for Wireless Personal Area Networks (WPANs)
Title	<b>Example of encoding a packet for the TVWS-FSK PHY</b>
Date Submitted	November 2013
Source	[ Cristina Seibert, Silver Spring Networks ] E-mail:[cseibert @ silverspringnet.com]
Re:	Comment Resolution for TG4m Letter Ballot
Abstract	This document presents example of the processing to generate TVWS-FSK packets.
Purpose	Example of packet encoding for the TVWS-FSK PHY
Notice	This document has been prepared to assist the IEEE P802.15. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
Release	The contributor acknowledges and accepts that this contribution becomes the property of IEEE and may be made publicly available by P802.15.

---

4  
5

**List of Tables**

1  
2  
3 **Table 1: PHR for scenario in this annex .....4**  
4

# Example encoding a packet for the TVWS-FSK PHY

## 1 Introduction

The purpose of this annex is to show examples of encoding a packet for the TVWS-FSK PHY, as described in 20.1. All features are enabled in order to provide data for each feature of the PHY, with the bit sequences shown at each processing step.

The message encoded is a PSDU of 7 octets shown below. The message constitutes an acknowledgment frame with a 3-octet MHR and a 4-octet FCS, as defined in 5.2.1.9. The bit sequence of the example PSDU is: 0100 0000 0000 0000 0101 0110 0101 1101 0010 1001 1111 1010 0010 1000

The encoding illustration goes through the following stages:

- a) Generating the bit sequence of the SHR.
- b) Generating the bit sequence of the PHR.
- c) Concatenating the PHR and tail bits, encoding and interleaving the concatenated sequence.
- d) Concatenating the PSDU, tail and pad bits, encoding and interleaving the concatenated sequence.
- e) Data whitening of the PSDU.
- f) Spreading of the encoded and interleaved PHR and of the encoded, interleaved and data whitened PSDU.
- g) Concatenation to form the PPDU.

The settings of the PIB attributes are also shown.

## 2 PIB Attribute Settings

For this example, selected PIB attributes are set as follows:

```
phyFSKPreambleLength=8  
phyTvwsSfdLength = 24  
phyFSKFECEnabled = TRUE  
phyTvwsFskFecScheme=0  
phyTvwsFskWhiteningEnabled=TRUE  
phyTvwsFskSpreadingEnabled=TRUE  
phyLECIMFSKSpreadingFactor=8  
phyLECIMFSKSpreadingPattern = NON_ALTERNATING
```

**3 Stage a)**

The bit sequence of the SHR, consisting of eight preamble octets and three SFD octets as described in 20.1.1.2, is given as:

```
0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 1100
0001 1000 1000 1101 0110
```

**4 Stage b)**

The Reserved field entry of the PHR is set to 0, the Ranging bit is set to 1, the FCS Type (FCS) field is set to (0) corresponding to a 4-octet FCS, the Data Whitening (DW) field is set to (1) (data whitening is used), and the Frame Length field entries are set to the binary representation of “7,” corresponding to the PSDU length of the packet. The Parity Check field is set to the XOR of all the other bits in the PHR, resulting in a value of 1. The complete PHR field is shown in Table 1:

**Table 1: PHR for scenario in this annex**

Bit string index	0	1	2	3	4	5-15
Bit mapping	R <sub>0</sub>	RNG	PC	FCS	DW	L <sub>10</sub> -L <sub>0</sub>
Field name	Reserved	Ranging	Parity Check	FCS Type	Data Whitening	Frame Length
Value	0	1	1	0	1	0 0 0 0 0 0 0 0 1 1 1

**5 Stage c)**

The PHR is concatenated with tail bits, and passed through the FEC encoder as described in 20.1.2.2. The resulting bit pattern is as follows:

```
0011 1010 1110 0110 1110 1100 0011 1001 0100 0101 0111
```

Subsequently, the coded sequence is interleaved as described in 20.1.2.2. The resulting bit pattern is as follows:

```
1011 1111 1001 0010 1111 0110 1101 0011 0011 0000 1000
```

**6 Stage d)**

1 The PSDU is concatenated with tail and pad bits, and passed through the FEC encoder described  
2 in 20.1.2.2. The bit sequence after convolutional coding is given as:

3  
4 0011 0111 1100 1011 0000 0000 0000 0000 0011 0100 1000 1101 1011 1101 1001 1100 0010  
5 0110 1001 1110 0111 0110 0000 1011 1010 0011 1110 1101 1110 1100 0000 0000 0000 0000  
6 0000 0000

7  
8 Interleaving is performed on the encoded PSDU as described in 20.1.2.2. The bit sequence after  
9 interleaving is given as:

10  
11 0111 0010 0100 1010 0101 1001 0100 0110 0001 0100 0101 1000 0100 1101 0011 1010 0011  
12 0010 0000 1100 0111 0011 0100 1110 0001 0000 1101 0010 0100 1001 0010 0100 0110 0010  
13 1000 1101

### 15 7 Stage e)

16  
17 Data whitening of the PSDU is performed as described in 20.1.2.3. The bit sequence after data  
18 whitening is given as:

19  
20 0111 1101 0011 1010 1110 1010 0010 1001 0101 0111 1100 0000 0000 0101 1001 0100 1000  
21 1110 1001 1011 0100 1011 0101 0011 1100 0011 0000 0110 1110 1001 0111 0001 0001 1111  
22 1110 0101

### 24 8 Stage f)

25  
26 Spreading of the encoded and interleaved PHR and encoded, interleaved and scrambled PSDU is  
27 performed as described in 20.1.2.4. The resulting bit sequence is as follows:

28 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 0100  
29 1110 1011 0001 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110  
30 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 0100  
31 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 0100 1110 1011 0001 1011 0001  
32 0100 1110 0100 1110 1011 0001 1011 0001 1011 0001 0100 1110 1011 0001 1011  
33 0001 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 1011 0001  
34 0100 1110 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 1011  
35 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001  
36 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 1011  
37 0001 0100 1110 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110  
38 0100 1110 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001 1011  
39 0001 1011 0001 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001  
40 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 1011

1 0001 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001  
2 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 1011 0001 1011  
3 0001 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 1011 0001 0100 1110  
4 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110 1011 0001 1011 0001 1011  
5 0001 1011 0001 0100 1110 0100 1110 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001  
6 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 1011  
7 0001 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 1011 0001  
8 1011 0001 0100 1110 1011 0001 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 0100  
9 1110 0100 1110 0100 1110 0100 1110 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001  
10 0100 1110

### 11 9 Stage g)

12

13 The sequence for the PPDU is given as:

14

15 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 0101 1100  
16 0001 1000 1000 1101 0110 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110  
17 0100 1110 0100 1110 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 1011 0001 0100  
18 1110 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110  
19 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 0100  
20 1110 1011 0001 1011 0001 0100 1110 0100 1110 1011 0001 1011 0001 1011 0001 1011 0001  
21 0100 1110 1011 0001 1011 0001 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 0100  
22 1110 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110  
23 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100 1110 1011  
24 0001 0100 1110 1011 0001 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001  
25 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001 0100 1110 0100  
26 1110 0100 1110 0100 1110 0100 1110 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001  
27 1011 0001 1011 0001 1011 0001 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 0100  
28 1110 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 1011 0001 1011 0001  
29 0100 1110 1011 0001 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 1011 0001 0100  
30 1110 1011 0001 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001  
31 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 1011 0001 0100  
32 1110 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 0100 1110 0100 1110 0100 1110  
33 1011 0001 1011 0001 1011 0001 1011 0001 0100 1110 0100 1110 1011 0001 1011 0001 1011  
34 0001 1011 0001 1011 0001 0100 1110 0100 1110 1011 0001 0100 1110 0100 1110 0100 1110  
35 1011 0001 0100 1110 1011 0001 1011 0001 0100 1110 1011 0001 0100 1110 0100 1110 0100  
36 1110 1011 0001 1011 0001 1011 0001 0100 1110 1011 0001 1011 0001 1011 0001 0100 1110  
37 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 0100 1110 1011 0001 1011  
38 0001 0100 1110 1011 0001 0100 1110