

TX Diversity with Array-Interference Gain

Date: 2013-07-16

Name	Company	Address	Phone	email
Gabriel Villardi	NICT	3-4 Hikarion-Oka, Yokosuka, Japan	+81-46-847-5438	gpvillardi@nict.go.jp
Pin-Hsun Lin	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		pslin@nict.go.jp
Zhang Xin	NICT	20 Science Park Road, #01-09A/10 TeleTech Park, Singapore		amy.xinzhang@ieee.org
Chang-Woo Pyo	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		cwpyo@nict.go.jp
Chunyi Song	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		songe@ieee.org
Masayuki Oodo	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		moodo@nict.go.jp
Keiichi Mizutani	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		songe@ieee.org
Hiroshi Harada	NICT	3-4, Hikarino-oka, Yokosuka, 239-0847, Japan		harada@ieee.org

Notice: This document has been prepared to assist IEEE 802.22. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.

Release: The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.22.

Patent Policy and Procedures: The contributor is familiar with the IEEE 802 Patent Policy and Procedures <http://standards.ieee.org/guides/bylaws/sh-bylaws.pdf> including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair [Wendong Hu](#) as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.22 Working Group. **If you have questions, contact the IEEE Patent Committee Administrator at patcom@ieee.org.**

Abstract

- **The objective the transmit (TX) diversity with array interference gain is to provide better link reliability than conventional techniques such as orthogonal space-time block codes (O-STBCs) [1]. Such scheme could be used to improve coverage area of IEEE 802.22b.**
- **Improvement over O-STBCs [1] comes from exploiting the energy contained in the MIMO array-interference.**
- **This can be achieved by designing the transmit vector in a way that interference is always constructive at the decoder side.**
- **We provide simulation results indicating significant performance improvements as compared to existing techniques.**

Alamouti [2] – 2TX

$$\mathbf{s} = \begin{bmatrix} s_1 \\ s_2 \end{bmatrix} \quad \mathcal{G}_2(\mathbf{s}) = \begin{bmatrix} s_1 & s_2 \\ -s_2^* & s_1^* \end{bmatrix} \quad \mathbf{h} = \begin{bmatrix} h_1 \\ h_2 \end{bmatrix} \quad \mathbf{w} = \begin{bmatrix} n_1 \\ n_2 \end{bmatrix}$$

$$\mathbf{r} = \begin{bmatrix} r_1 \\ r_2 \end{bmatrix} = \mathcal{G}_2 \cdot \mathbf{h} + \mathbf{w} \quad \text{(Received Open-Loop Alamouti signal)}$$

By doing the proper combination with “r” (skipped here for simplicity), the estimated symbol vector is:

$$\hat{\mathbf{s}} = \mathbf{D} \cdot \mathbf{s} + \bar{\mathbf{w}} = \begin{bmatrix} |h_1|^2 + |h_2|^2 & 0 \\ 0 & |h_1|^2 + |h_2|^2 \end{bmatrix} \cdot \begin{bmatrix} s_1 \\ s_2 \end{bmatrix} + \begin{bmatrix} \bar{w}_1 \\ \bar{w}_2 \end{bmatrix}$$

Diversity factor No Interference (Orthogonal)
No Interference (Orthogonal) Diversity factor

Generating Interference by Spanning Alamouti over 4 TX antennas

$$\mathcal{G}_4(\mathbf{s}) = \begin{bmatrix} \boxed{\begin{matrix} s_1 & s_2 \\ -s_2^* & s_1^* \\ \text{Alamouti} \end{matrix}} & \boxed{\begin{matrix} s_1 & s_2 \\ -s_2^* & s_1^* \\ \text{Alamouti} \end{matrix}} \end{bmatrix} \quad \mathbf{h} = \begin{bmatrix} h_1 \\ h_2 \\ h_3 \\ h_4 \end{bmatrix} \quad \mathbf{w} = \begin{bmatrix} w_1 \\ w_2 \end{bmatrix}$$

$$\mathbf{r} = \begin{bmatrix} r_1 \\ r_2 \end{bmatrix} = \mathcal{G}_4 \cdot \mathbf{h} + \mathbf{w}$$

By doing the proper combination with “r” (skipped here for simplicity), the estimated symbol vector is:

Same Diversity factor of 4TX STBC + generated interference


Orthogonal

$$\hat{\mathbf{s}} = \mathbf{D} \cdot \mathbf{s} + \bar{\mathbf{w}} = \begin{bmatrix} \boxed{\begin{matrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ -(h_1^* h_3 + h_1 h_3^* + h_2^* h_4 + h_2 h_4^*) \end{matrix}} & \boxed{0} \\ \boxed{0} & \boxed{\begin{matrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ -(h_1^* h_3 + h_1 h_3^* + h_2^* h_4 + h_2 h_4^*) \end{matrix}} \end{bmatrix} \cdot \begin{bmatrix} s_1 \\ s_2 \end{bmatrix} + \begin{bmatrix} \bar{w}_1 \\ \bar{w}_2 \end{bmatrix}$$

Same Diversity factor of 4TX STBC + generated interference

Generating Interference by Spanning Alamouti over 4 TX antennas

- The problem is that the generated interference bellow
 $-(h_1^* h_3 + h_1 h_3^* + h_2^* h_4 + h_2 h_4^*) = -(2\text{Re}\{h_1 h_3 + h_2 h_4\})$
assumes “positives” and “negative” values with the same probability due
to its pdf being:




Generating Interference by Spanning Alamouti over 4 TX antennas

- The interference causes the diversity gain bellow (which is always “positive”) to sometimes increase and reduce its value.

$$|h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2$$

- The resultant is a final diversity similar to open loop Alamouti.



Alamouti with Array-Interference Gain (4 TX Antennas)

- Since the interference is composed by channel values, and the receiver (RX) can estimate the channel with a high precision, the receiver knows when the interference is being “constructive” or “destructive”.
- The idea is to make the interference **ALWAYS constructive** (positive). In order to do it, we have to manipulate the transmit scheme in the following manner:

$$\bar{\mathcal{G}}_4(\mathbf{s}) = \begin{bmatrix} s_1 & s_2 & s_1 & s_2 \\ -s_2^* & s_1^* & -s_2^* & s_1^* \end{bmatrix} \quad \text{Whenever interference is “+”}$$

$$\bar{\bar{\mathcal{G}}}_4(\mathbf{s}) = \begin{bmatrix} s_1 & s_2 & -s_1 & -s_2 \\ -s_2^* & s_1^* & s_2^* & -s_1^* \end{bmatrix} \quad \text{Whenever interference is “-”}$$

Alamouti with Array-Interference Gain (4 TX Antennas)

- Since 802.22b system supports TDD, both TX and RX obtain CSI due to channel reciprocity.
- By doing the necessary manipulations with the received signal (skipped here for the sake of simplicity), the estimated symbol vector is given by:


Diversity factor + absolute value of interference

$$\hat{\mathbf{s}} = \mathbf{D} \cdot \mathbf{s} + \bar{\mathbf{w}} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 + \text{abs}(h_1^* h_3 + h_1 h_3^* + h_2^* h_4 + h_2 h_4^*) & 0 \\ 0 & |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 + \text{abs}(h_1^* h_3 + h_1 h_3^* + h_2^* h_4 + h_2 h_4^*) \end{bmatrix} \cdot \begin{bmatrix} s_1 \\ s_2 \end{bmatrix} + \begin{bmatrix} \bar{w}_1 \\ \bar{w}_2 \end{bmatrix}$$

Diversity factor + absolute value of interference


Alamouti with Array-Interference Gain (4 TX Antennas)

- The interference is always constructive (positive) owing to the fact that choosing the proper transmit matrix, the interference pdf becomes:



Alamouti with Array-Interference Gain

- BER performance



Creating Further Interference Over 4TX Antennas

- In fact, Alamouti [2] is not the best scheme to span over TX antennas. The best scheme should be the one that generates more interference, so we can align then to increase the overall gain.
- In order to generate more interference, it is necessary to span a single symbol “s” over the TX antennas and do the proper received signal manipulation (skipped here for simplicity).
- Following the same line of thought, generate all possible dissimilar TX matrices:

$$\mathcal{G}_{4_1} = \begin{bmatrix} s & s & s & s \end{bmatrix}$$

$$\mathcal{G}_{4_2} = \begin{bmatrix} s & -s & s & -s \end{bmatrix}$$

$$\mathcal{G}_{4_3} = \begin{bmatrix} s & s & -s & -s \end{bmatrix}$$

$$\mathcal{G}_{4_4} = \begin{bmatrix} s & -s & -s & s \end{bmatrix}$$

$$\mathcal{G}_{4_5} = \begin{bmatrix} s & s & s & -s \end{bmatrix}$$

$$\mathcal{G}_{4_6} = \begin{bmatrix} s & s & -s & s \end{bmatrix}$$

$$\mathcal{G}_{4_7} = \begin{bmatrix} s & -s & s & s \end{bmatrix}$$

$$\mathcal{G}_{4_8} = \begin{bmatrix} -s & s & s & s \end{bmatrix}$$

Creating Further Interference Over 4TX Antennas

- After doing the necessary manipulation (skipped for simplicity), each TX vector yields a specific estimated symbol:

$$\textcircled{1} \mathcal{G}_{4_1} = \begin{bmatrix} s & s & s & s \end{bmatrix}$$

$$\hat{s} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(h_1^*h_2 + h_1h_2^* + h_1^*h_3 + h_1h_3^* + h_1^*h_4 + h_1h_4^* + h_2^*h_3 + h_2h_3^* + h_2^*h_4 + h_2h_4^* + h_3^*h_4 + h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₁)

$$\textcircled{2} \mathcal{G}_{4_2} = \begin{bmatrix} s & -s & s & -s \end{bmatrix}$$

$$\hat{s} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(-h_1^*h_2 - h_1h_2^* + h_1^*h_3 + h_1h_3^* - h_1^*h_4 - h_1h_4^* - h_2^*h_3 - h_2h_3^* + h_2^*h_4 + h_2h_4^* - h_3^*h_4 - h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₂)

$$\textcircled{3} \mathcal{G}_{4_3} = \begin{bmatrix} s & s & -s & -s \end{bmatrix}$$

$$\hat{s} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(h_1^*h_2 + h_1h_2^* - h_1^*h_3 - h_1h_3^* - h_1^*h_4 - h_1h_4^* - h_2^*h_3 - h_2h_3^* - h_2^*h_4 - h_2h_4^* + h_3^*h_4 + h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₃)

Creating Further Interference Over 4TX Antennas

$$\mathcal{G}_{44} = \begin{bmatrix} s & -s & -s & s \end{bmatrix}$$

$$\hat{\mathbf{s}} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(-h_1^*h_2 - h_1h_2^* - h_1^*h_3 - h_1h_3^* + h_1^*h_4 + h_1h_4^* + h_2^*h_3 + h_2h_3^* - h_2^*h_4 - h_2h_4^* - h_3^*h_4 - h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₄)

$$\mathcal{G}_{45} = \begin{bmatrix} s & s & s & -s \end{bmatrix}$$

$$\hat{\mathbf{s}} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(h_1^*h_2 + h_1h_2^* + h_1^*h_3 + h_1h_3^* - h_1^*h_4 - h_1h_4^* + h_2^*h_3 + h_2h_3^* - h_2^*h_4 - h_2h_4^* - h_3^*h_4 - h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₅)

$$\mathcal{G}_{46} = \begin{bmatrix} s & s & -s & s \end{bmatrix}$$

$$\hat{\mathbf{s}} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(h_1^*h_2 + h_1h_2^* - h_1^*h_3 - h_1h_3^* + h_1^*h_4 + h_1h_4^* - h_2^*h_3 - h_2h_3^* + h_2^*h_4 + h_2h_4^* - h_3^*h_4 - h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₆)

Creating Further Interference Over 4TX Antennas

$$\mathcal{G}_{47} = \begin{bmatrix} s & -s & s & s \end{bmatrix}$$

$$\hat{s} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(-h_1^*h_2 - h_1h_2^* + h_1^*h_3 + h_1h_3^* + h_1^*h_4 + h_1h_4^* - h_2^*h_3 - h_2h_3^* - h_2^*h_4 - h_2h_4^* + h_3^*h_4 + h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₇)

$$\mathcal{G}_{48} = \begin{bmatrix} -s & s & s & s \end{bmatrix}$$

$$\hat{s} = \begin{bmatrix} |h_1|^2 + |h_2|^2 + |h_3|^2 + |h_4|^2 \\ \underline{(-h_1^*h_2 - h_1h_2^* - h_1^*h_3 - h_1h_3^* - h_1^*h_4 - h_1h_4^* + h_2^*h_3 + h_2h_3^* + h_2^*h_4 + h_2h_4^* + h_3^*h_4 + h_3h_4^*)} \end{bmatrix} \cdot [s] + [\bar{w}]$$

Interference (I₈)

Conclusions

- **Improved link reliability compared to the one of existing techniques can be earned by wisely exploiting the MIMO array interference. A natural consequence of utilizing such scheme is to increase of coverage area in IEEE 802.22b.**
- **The proposed scheme is full rate and full diversity + array interference gain, which results in improved link reliability even if compared to ideal 4TX antennas STBC.**
- **The proposed schemes makes use of the channel reciprocity inherent to TDD systems to as to estimate CSI and then design the transmit vector which yields the best constructive interference.**

References

- [1] V. Tarok, H. Jafarkhani. and A.R. Calderbank, "Space-time block codes fmm orthogonal designs," *IEEE Tmns. on Infymativn ntro!y*, vol. 45. no. 5. pp. 1456-1467, July 199
- [2] S.M. Alamouti. "A simple Wnsmitter diversity scheme for wireless com- munications," *IEEE Joumol on Selected Arcas in Communications*, vol. SAC-16, pp. 1451-1458, OCTObw 1998.